

Temp C	Copper at 100% Conductivity		Temp C	1350 Aluminum Alloy		Temp C	8176 Aluminum Alloy	
	To Correct Resistance to 20 C Multiply by	To Convert Resistance @ 20 C to Known Temp Multiply by		To Correct Resistance to 20 C Multiply by	To Convert Resistance @ 20 C to Known Temp Multiply by		To Correct Resistance to 20 C Multiply by	To Convert Resistance @ 20 C to Known Temp Multiply by
15	1.01965	0.98035	15	1.02040	0.97960	15	1.02015	0.97985
16	1.01572	0.98428	16	1.01632	0.98368	16	1.01612	0.98388
17	1.01179	0.98821	17	1.01224	0.98776	17	1.01209	0.98791
18	1.00786	0.99214	18	1.00816	0.99184	18	1.00806	0.99194
19	1.00393	0.99607	19	1.00408	0.99592	19	1.00403	0.99597
20	1.00000	1.00000	20	1.00000	1.00000	20	1.00000	1.00000
21	0.99607	1.00393	21	0.99592	1.00408	21	0.99597	1.00403
22	0.99214	1.00786	22	0.99184	1.00816	22	0.99194	1.00806
23	0.98821	1.01179	23	0.98776	1.01224	23	0.98791	1.01209
24	0.98428	1.01572	24	0.98368	1.01632	24	0.98388	1.01612
25	0.98035	1.01965	25	0.97960	1.02040	25	0.97985	1.02015
26	0.97642	1.02358	26	0.97552	1.02448	26	0.97582	1.02418
27	0.97249	1.02751	27	0.97144	1.02856	27	0.97179	1.02821
28	0.96856	1.03144	28	0.96736	1.03264	28	0.96776	1.03224
29	0.96463	1.03537	29	0.96328	1.03672	29	0.96373	1.03627
30	0.96070	1.03930	30	0.95920	1.04080	30	0.95970	1.04030
31	0.95677	1.04323	31	0.95512	1.04488	31	0.95567	1.04433
32	0.95284	1.04716	32	0.95104	1.04896	32	0.95164	1.04836
33	0.94891	1.05109	33	0.94696	1.05304	33	0.94761	1.05239
34	0.94498	1.05502	34	0.94288	1.05712	34	0.94358	1.05642
35	0.94105	1.05895	35	0.93880	1.06120	35	0.93955	1.06045
36	0.93712	1.06288	36	0.93472	1.06528	36	0.93552	1.06448
37	0.93319	1.06681	37	0.93064	1.06936	37	0.93149	1.06851
38	0.92926	1.07074	38	0.92656	1.07344	38	0.92746	1.07254
39	0.92533	1.07467	39	0.92248	1.07752	39	0.92343	1.07657
40	0.92140	1.07860	40	0.91840	1.08160	40	0.91940	1.08060